



**WEBDYN INDIA**


SIGNAL CONVERTER



## 4/8 CHANNEL DIN-Rail ANALOG INPUT MODULE MODBUS OVER RS485 SERIAL INTERFACE

### TECHNICAL SPECIFICATIONS

Description	ANALOG INPUT MODULES MODBUS M100 4AI
Input	0-20A, 4-20 mA
Accuracy	±0.25% of reading
Zero offset	user adjustable over full range for each channel
Sampling	100mS per channel
Port	RS485,2 wire
Protocol	Modbus RTU
Baud rate settable	2400, 4800, 9600, 19200, 38400, 57600, 115200
Parity settable	none, even, odd
Supply operated	20~32 VDC
Reference	M100 4AI



# ***WEBDYN INDIA***



***WEBDYN***

## **INDIA**



2ND FLOOR, PERCEPT HOUSE - 1,  
SANT NAGAR, EAST OF KAILASH  
NEW DELHI 110 065



+91 11 41519011



GURDEEP.JUNEJA@WEBDYN.COM

## **FRANCE**



26 RUE DES GAUDINES  
78100  
SAINT GERMAIN EN LAYE



+33 139 042 940



CONTACT@WEBDYN.COM